

VARI***LITE**®

TECHNICAL NOTICE

PRODUCT: VL3500™ Wash Luminaires

SUBJECT: Pack-Up Cues and Console Default States for Shipping VL3500™ Wash Luminaires

OVERVIEW

To prepare VL3500™ Wash Luminaires for shipment, Vari-Lite recommends specific pack up cue and console default values. In particular, to minimize the possibility of damage during transport, set the DMX values for **VARI*BRITE™** and **Zoom to 0 (zero)** prior to shipment. For the complete list of all recommended DMX shipping default values, see the table in this notice.

The DMX values in "[Pack-up Cues and Console Default States for VL3500™ Wash Luminaires](#)" should be included as the default settings for console profiles. If these values are set as the console default states, a simple release of the fixture initiates the pack-up cue.

If a particular console does not set the VL3500™ Wash Luminaires to these default values, Vari-Lite strongly recommends the creation of a “pack-up” cue that, at the least, sets VARI*BRITE™ and Zoom values to 0, and preferably sets all of the default values recommended in this notice.

If you have any questions as to any aspect of this Technical Notice, please contact Vari-Lite customer service at 1-877-VARILITE or +1-214-647-7880.



WARNING: Any repairs or maintenance to Vari-Lite luminaires should only be performed by a trained and qualified service technician or at an Authorized VARI***LITE**® Service facility.

PACK-UP CUES AND CONSOLE DEFAULT STATES FOR VL3500™ WASH LUMINAIRES

DMX Channel	Parameter	Recommended Default Value
1	Intensity	0
2	Hi Byte Pan	32768 (mid position)
3	Lo Byte Pan	
4	Hi Byte Tilt	32768 (mid position)
5	Lo Byte Tilt	
6	VARI*RITE™ Mode	0 (closed)
7	Zoom	0 (narrow)
8	CTO Mixer	0 (open)
9	Cyan (Blue) Mixer	0 (open)
10	Yellow (Amber) Mixer	0 (open)
11	Magenta Mixer	0 (open)
12	Color Wheel 1	0
13	Color Wheel 2	0
14	Strobe	0 (open)
15	Aperture Wheel	0
16	Focus Time	255
17	Color Time	255
18	Beam Time	255
19	Control Channel	0

CONTACT INFORMATION

For more information on this technical notice or on VARI*RITE® products, please contact your Authorized VARI*RITE® Dealer or Vari-Lite customer service.